



The LG EzSign TV LED Commercial Widescreen

55LN549E
55" class (54.6" measured diagonally)
47LN549E
47" class (46.9" measured diagonally)
42LN549E
42" class (41.9" measured diagonally)
39LN549E

39" class (38.5" measured diagonally)

▶ 32LN549E

32" class (31.5" measured diagonally)



Digital Signage + Television : Billboard TV

The LG EzSign TV is the world's first TV that comes with a signage function. Run messages on the TV screen in the form of a billboard without additional hardware. Advertisements, information and broadcast content can be arranged on the same screen to attract attention and deliver specific messaging to your customer base.

COST EFFECTIVE

No need to buy a media player - Create your own signage content by using your PC and the free EzSign TV software. Transfer that content by using a USB flash drive and plug it in to the EzSign TV to run it.

CUSTOMIZED TO YOUR NEEDS

Signage content can be customized for your business - The LG EzSign TV allows you to create your own signage content and make revisions on the fly.

FAST AND EASY

Edit content quickly and easily - Select one of the pre-made templates. Add your images and text to it. It's that simple.

\$

Choose from a broad range of template designs - The LG EzSign TV gives you the power to choose and change according to your needs.



The Best Award Winner (two consecutive years) from the Commercial Integrator magazine for digital signage hardware and the product of the year from CRN, the LG EzSign TV is an innovation in digital signage that can entertain while maximizing the impact of your message.



LG EzSign TV Free Software v2.0

CREATE YOUR CONTENT IN 4 SIMPLE STEPS



Choose from a wide array of pre-installed templates.



Schedule events.

FREE TEMPLATES*

56 high quality FREE templates are available that can easily be updated. * Templates can not be modified.



ENTER TEXT EASILY Created by LG, this program offers the click-and-write function, easy even for beginners.



Add text and drag and drop your image files into the content boxes.



Export your content to the TV via USB or Wirelessly.

ADD PHOTOS

Take or upload photos at the business site and insert into a template.



FOR EFFICIENT MANAGEMENT

PUBLIC DISPLAY MODE

From channel selection to energy-saving features, Public Display Mode allows you to control the TV settings in your business area prevent misuse by customers, set volume limits, or restore factory defaults on any TV. You are in control of it all.



USB CLONING

The USB Cloning feature allows you to simply copy the TV settings onto all TVs using a USB stick, a process that is fully automated to save time without having to set each TV one by one.





Public Display

WELCOME SCREEN Welcome visitors with a warm greeting message that includes your business name and logo.



Multi IR function eliminates the remote control signal interference between TVs in multiple dwelling rooms. This system will work using the same LG TV model. (Optional 124-213-10 required)





RS232C CONTROL

Via the TV's RS-232C port, you can remotely control multiple TVs' power and volume settings simultaneously.



FOR CONVENIENCE & ENTERTAINMENT

EXTERNAL SPEAKER OUT

Enhance the entertainment experience by adding an additional speaker, visitors to listen to and control the TV audio from anywhere in your business area, including restrooms.





REMOTE JACK PACK

The plug and play function with compatible Remote Jack Pack enables guests to view media from their portable devices on the TV screen seemlessly.



IR OUT

IR Out enables customized set-top boxes to receive IR signals via LG TV Signage. This added convenience requires only simple connections and allows easy management using a single remote control.





USB 2.0

You can play images and videos from and record TV programs to external storage devices. Immediate recording and reserved recording options are available.





when it's green.

LG is committed to improving product development, manufacturing and usage to meet the demand for products with environmentally friendlier features. Our televisions have technologies to reduce power consumption and in return increase cost savings per room.

EcoSmart

- Energy Saving Levels Manually select your choice for the brightness level for the television.
- CEC Compliant Meets the Appliance Efficiency Regulations of the California Energy Commission.
- RoHS Compliant Meets directive on restriction of hazardous substances. •
- Energy Star 6.0 Qualified Meets current reduction requirements of energy • consumption.







400mm 47LN549 200mm 42LN549E

. 00mm 47LN549E

42LN549

1 / ADDA

47LN549E/42LN549E



0.4" 47LN549E 9.3" 42LN549E

- 11.7





HOMIN / DVI N 2 _____ OPTICA

¢.....) RS-232C IN (CONTROL & SERVICE



81" 32I N549F

ANTENNA/ CABLE IN \odot

AV IN

0 O

0



Rear Jack Panel

The LG EzSign TV

LED Commercial Widescreen

▶ 55LN549E

55" class (54.6" measured diagonally)



▶ 47LN549E

47" class (46.9" measured diagonally)

▶ 42LN549E

42" class (41.9" measured diagonally)

▶ 39LN549E

39" class (38.5" measured diagonally)

> 32LN549E

32" class (31.5" measured diagonally)

PANEL	Model	55LN549E	47LN549E	42LN549E	39LN549E	32LN549E	INPUTS/	Model	55LN549E	47LN549E	42LN549E	39LN549E	32LN549E	
	Backlighting	Direct LED					OUTPUTS	USB (2.0)		2 Side (1 for Wifi-Dongle)				
	LCD Panel Type	55" Class (5 4 4")	47" Class (46 0)	42" Class (41.9")	20" Class (20 E)	20" Class (21 5")		RF In	1 Rear					
	(measured diagonally)	JJ Cluss (J4.0)	. ,		39 Class (30.3)			AV In	1 Rear					
	Native Resolution	1920 x 1080 (FHD) 1366 x 768 (HD)						Digital Audio Out	Coaxial / Optical)					
	Brightness	300cd/m ²												
	Dynamic CR Viewing Angle (HxV)	1,000,000:1						HDMI/HDCP Input	3 (2 Rear, 1 Side)					
	Response Time	9ms 9.5ms 9ms						RGB In (D-sub 15pin) - PC	1 Rear					
	Frame Rate	60Hz						PC Audio Input		1 (Sharing with AV In)				
VIDEO	Built-In Tuner	ATSC/NTSC/Clear QAM						RS-232C (D-Sub	1 Rear 1 Rear					
	XD Engine	Yes						9pin)						
	24p Real Cinema (24p 5:5/2:2 Pull down)	Yes						RJ45 (RJP interface)						
	Eye Care (Anti Dazzling)	Yes						External Speaker Out (3.5mm phone jack)		1 Rear				
AUDIO	Audio Output Speaker System	20W (10W x 2) 1 Way 2 Speakers					CABINET	Bezel Width (off Bezel) (mm)	18.7mr	n, 23.3mm	17.3mm, 21.9mm	18.9mm, 23.5mm	18.7mm, 23.3mm	
	Infinite Sound	Yes						With Stand	49.2" x 31.1" x 11.7"	42.5″ x 27.3″ x 10.4′	38.1″ x 24.8″ x 9.3″	35.2" x 23.1" x 9.3"	29.1″ x 19.6″ x 8.1″	
	Invisible Speaker	Yes					1	Weight	46.7 lbs.	32.0 lbs.	23.6 lbs.	21.4 lbs.	15.4 lbs.	
	Clear Voice II	Yes						Without Stand	49.2" x 29.0" x 3.1"	42.5" x 25.3" x 3.2"	38.1" x 22.8" x 3.1"	35.2" x 21.1" x 3.1"	29.1″ x 177″ x 3.1″	
SPECIAL	RF(1/2Tuner)	Yes (1 Tuner)						Weight	42.1 lbs	28.9 lbs	21.2 lbs	18.9 lbs	14.1 lbs	
FEATURES	Simplink	Yes (HDMI-CEC)						Carton	61.0"×33.1"×8.3"	52.4" x 29.5" x 6.9"	45.3" x 26.0" x 6.9"	42.3" x 25.2" x 6.5"	35.5" x 20.9" x 6.4"	
	SI Compatible	Yes (TV Link Tuner)						Weight	59.5 lbs.	40.6 lbs.	31.3 lbs.	28.2 lbs.	20.3 lbs.	
	(TVLink Protocol)	· · · · ·						Swivel		±90° Black with Hairline Finish			±15°	
	WiFi	Optional LG USB dongle (AN-WF100)						Color						
	Hotel Mode/ PDM /Installer Menu	Yes						VESA™ Standard Mount Interface	400mm	n x 400mm	200mm x 200mm		200mm x 100mm	
	IR Out	Yes (RS-232C)						Credenza Bracket	Yes	Yes	Yes	Yes	No	
	External Speaker Out	Yes (Variable/Fixed/Line Out, 3.5mm, Stereo, Single ended Type(GRD,L+,R+), 1W with 8Ω)						Flame Retardant		Yes (Back Cover only)				
	RJP Interface	Yes (RJ45, HDMI)					REQUIRED LISTINGS	Safety	cUL, UL, NOM, FCC					
	RJP Compatibility	LG,Teleadapt (RJ45, HDMI CEC), G-Link(HDMI-CEC)					LISTINGS	RoHS	Yes					
	USB	USB2.0, USB Auto Play back, USB Cloning						Energy Star 6.0	Yes					
	Moving Picture Playback	Divx HD					UPC POWER	0,	7 19192 90448 4	4 7 19192 90447 7 7 19192 90446 0 7 19192 91560 2 7 100~240V 50/60Hz			7 19192 90444 6	
	(SD/HD/Plus HD) Picture	IPEG						Power Source Watts (Typical)	82W	70W	55W	48W	41.1W	
		5. = -						Stand-by	0277	7000		4877 0.5W	41.1 VV	
	Audio Codec	AC3(Dolby Digital), EAC3, AAC, Mpeg, MP3, PCM					WARRANTY	/	ar Limited Warranty (Parts/Labor/Backlight)					
	USB Cloning	USB 2.0						z rear Linnieu vvarranny (rans/ Labor/ backligni)						
	Multi IR Code Welcome Screen	Yes Yes												
	(Splash Image) Auto Off / Auto	Yes												
	Sleep Video Mute	Yes												
								Required I	PC spec for i	nstallation [.] Pe	ntium M or 4	CPU, 512MB	RAM.	
	Smart Energy Saving	Yes					Required PC spec for installation: Pentium M or 4 CPU, 512MB RAM, Windows XP sp2, 200MB HDD							
	Anti-theft System	Kensington Lock						O						
	Credenza	Yes												

The estimated annual energy cost determined in accordance with 16 CFR Part 305.5 for models 55LN549E, 47LN549E, 42LN549E, 39LN549E and 32LN549E are \$17, \$14, \$11, \$10 & \$9 respectively. "Your energy cost depends on your utility rates and use. The estimated cost is based on 11 cents per kWh and 5 hours of use per day. For more information, visit www.frc.gov/energy." FTC Television labeling rule (18 CFR Part 305, as added by 76 Fed. Reg. 1038 (Jan 6, 2011)).

Wi-Fi READY SMART SCHEDULING USB 🕫 🚯 Watcome - 600 · USB Energy нот



All screen images are simulated. Dimensions and weights are approximate. Design, features and specifications subject to change without notice

© Copyright 2013 LG Electronics USA, Inc. All Rights Reserved. "LG Life's Good" is a registered trademark of LG Corp. XD Engine is a registered trademark of LG Electronics, Inc. HealthView and EcoSmart are trademarks of LG Corp. ENERGY STAR is a registered trademark of the U.S. Environmental Protection Agency.Dolby and the double-D symbol are registered trademarks of Dolby Laboratories. SRS and the SRS symbol, TruSurround XT and WOW are trademarks or registered trademarks of SRS Labs, Inc. VESA is a trademark of Video Electronics Standards Association. All other product and brand names are trademarks or registered trademarks of their respective companies.

Life's Good LGsolutions.com

Bracket

ENERGY

GUIDE

HE B2B Division 2000 Millbrook Drive Lincolnshire, IL 60069

LG Electronics U.S.A., Inc.

Customer Service: 888.865.3026 www.LGsolutions.com/support

Contact your LG Regional Sales Representative: Channel: 800.897.8871 Hospitality: 800.228.1236 E-mail: info@LGsolutions.com

SPEC_LN549E_041310_PR

Printed in the USA. May 2013